

# MA8000 integrated amplifier

- High power, 300 watt per channel stereo amplifier - enough power to properly run any speaker type.
- Analog eight band tone control allows for precision adjustment so your recordings sound their best.
- Moving Coil and Moving Magnet phono inputs feature adjustable cartridge loading and impedance matching, assuring every turntable gives its optimal performance when played through the MA8000.
- Five digital inputs allow the McIntosh Digital Engine to decode your digital music at up to 32 bits and 192kHz for maximum analog fidelity and enjoyment.
- The Home Theater Passthru feature allows for seamless integration of multi-channel systems with the MA8000's power and precision sound.
- The High Drive headphone amplifier will match any headphones between 20 and 600 ohms, allowing for the ultimate personal listening experience.



Monumental Performance

McIntosh®

LEGENDARY PERFORMANCE™

[www.mcintoshlabs.com](http://www.mcintoshlabs.com)

# MA8000 integrated amplifier

## Amplifier Power Output:

300 watts per channel with both channels operating into 2, 4 or 8 Ohms, with Power Meters

## Total Harmonic Distortion:

0.005% maximum from 20Hz to 20kHz

## Preamplifier Inputs:

Six high level unbalanced  
Two high level balanced  
Two Phono: one Moving Coil and one Moving Magnet (both adjustable loading)  
Five digital inputs

## Digital Section:

Five digital inputs: one dedicated USB, and four assignable: two coax and two optical PCM  
McIntosh Digital Engine is 32 bit 192kHz, USB 2.0 asynchronous

## Tone Controls:

Discrete/manual/analog eight band EQ

## High Drive Headphone Amplifier:

All headphones, from 20 to 600 Ohms

## Home Theater Pass Through:

Allows interfacing with a Home Theater system

## Overall Dimensions (W x H x D):

17-1/2" (44.5cm) x 9-7/16" (24 cm) x 22" (55.88cm) including knobs, connectors and cables

## Weight:

100 lbs (45.4kg) net,  
133 lbs (60.3kg) in shipping carton



## For the Consumer's Protection:

In order to ensure the highest level of customer satisfaction, new McIntosh products may only be purchased from an Authorized McIntosh Dealer; and, with certain limited exceptions may only be purchased over-the-counter or delivered and installed by the Authorized McIntosh Dealer. McIntosh does not warrant, in any way, products that are purchased from anyone who is not an Authorized McIntosh Dealer, or that have had their serial numbers altered or defaced.



## Companion Products

The McIntosh MR88 AM/FM/HD Tuner, MCD550 SACD/CD Player, MT10 Turntable, XR100 Loudspeakers, MEN220 Room Correction System and MPC1500 Power Controller are logical companions for the MA8000 Integrated Amplifier. Your Authorized Dealer can provide additional information on other McIntosh product combinations.

To learn more, please call us at 1.800.538.6576.

# McIntosh®

LEGENDARY PERFORMANCE™

www.mcintoshlabs.com